

DF102

TeSys fuse-disconnector 2P 32A - fuse size 10 x 38 mm



Main

| | |
|---------------------------|-------------------|
| Range | TeSys |
| Product name | TeSys DF |
| Product or component type | Fuse-disconnector |
| Device short name | DF10 |
| Poles description | 2P |

Complementary

| | |
|--|---|
| Mounting support | Rail |
| Mounting position | Vertical +/- 23° |
| Control type | Toggle |
| [Ie] rated operational current | 32 A for power circuit |
| [Uimp] rated impulse withstand voltage | 6 kV |
| Fire resistance | 960 °C conforming to IEC 60695-2-1 |
| [Ipk] rated peak withstand current | 15 kA with tubular links conforming to IEC 60269-1 |
| Short-circuit withstand | 120 kA 400 V conforming to IEC 60947-3 120 kA 500 V conforming to IEC 60947-3 |
| Fuse size | 10 x 38 mm |
| Fuse type | AM GG |
| [Ui] rated insulation voltage | 690 V for power circuit AC 690 V for power circuit DC |
| Connections - terminals | 1 solid cable(s) 1.5...16 mm ² on screw clamp terminals for power circuit 2 solid cable(s) 1.5...6 mm ² on screw clamp terminals for power circuit 1 flexible cable(s) 1.5...10 mm ² without cable end on screw clamp terminals for power circuit 2 flexible cable(s) 1.5...6 mm ² without cable end on screw clamp terminals for power circuit 1 flexible cable(s) 1.5...10 mm ² with cable end on screw clamp terminals for power circuit 2 flexible cable(s) 1.5...6 mm ² with cable end on screw clamp terminals for power circuit |
| Tightening torque | 2.2 N.m power circuit : on screw clamp terminals |
| Quantity per set | Set of 6 |

Environment

| | |
|---------------------------------------|--|
| Standards | IEC 60947-3 UL 512 CSA C22.2 No 39 |
| Product certifications | UR |
| IP degree of protection | IP20 conforming to IEC 60529 |
| Protective treatment | TH |
| Ambient air temperature for storage | -40...80 °C |
| Ambient air temperature for operation | -20...60 °C with derating |
| Height | 88.5 mm |
| Width | 35 mm |
| Depth | 64 mm |
| Product weight | 0.122 kg |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

